

NAG Library Routine Document

C06PCF

Note: before using this routine, please read the Users' Note for your implementation to check the interpretation of ***bold italicised*** terms and other implementation-dependent details.

1 Purpose

C06PCF calculates the discrete Fourier transform of a sequence of n complex data values (using complex data type).

2 Specification

```
SUBROUTINE C06PCF(DIRECT, X, N, WORK, IFAIL)
  INTEGER          N, IFAIL
  complex*16      X(N), WORK(*)
  CHARACTER*1      DIRECT
```

3 Description

Given a sequence of n complex data values z_j , for $j = 0, 1, \dots, n-1$, C06PCF calculates their (**forward** or **backward**) discrete Fourier transform defined by

$$\hat{z}_k = \frac{1}{\sqrt{n}} \sum_{j=0}^{n-1} z_j \times \exp\left(\pm i \frac{2\pi jk}{n}\right), \quad k = 0, 1, \dots, n-1.$$

(Note the scale factor of $\frac{1}{\sqrt{n}}$ in this definition.) The minus sign is taken in the argument of the exponential within the summation when the forward transform is required, and the plus sign is taken when the backward transform is required.

A call of C06PCF with DIRECT = 'F' followed by a call with DIRECT = 'B' will restore the original data.

C06PCF uses a variant of the fast Fourier transform (FFT) algorithm (see Brigham (1974)) known as the Stockham self-sorting algorithm, which is described in Temperton (1983).

4 References

Brigham E O (1974) *The Fast Fourier Transform* Prentice-Hall

Temperton C (1983) Self-sorting mixed-radix fast Fourier transforms *J. Comput. Phys.* **52** 1–23

5 Parameters

- 1: DIRECT – CHARACTER*1 *Input*
On entry: if the forward transform as defined in Section 3 is to be computed, then DIRECT must be set equal to 'F'.
 If the backward transform is to be computed then DIRECT must be set equal to 'B'.
Constraint: DIRECT = 'F' or 'B'.
- 2: X(N) – **complex*16** array *Input/Output*
On entry: if X is declared with bounds (0 : N – 1) in the subroutine from which C06PCF is called, then X(j) must contain z_j , for $j = 0, 1, \dots, n-1$.

On exit: the components of the discrete Fourier transform. If X is declared with bounds $(0 : N - 1)$ in the subroutine from which C06PCF is called, then for $0 \leq k \leq n - 1$, $\hat{z}_k$ is contained in $X(k)$.

3: N – INTEGER *Input*

On entry: n , the number of data values. The total number of prime factors of N , counting repetitions, must not exceed 30.

Constraint: $N \geq 1$.

4: $WORK(*)$ – **complex*16** array *Workspace*

Note: the dimension of the array $WORK$ must be at least $2 \times N + 15$.

The workspace requirements as documented for C06PCF may be an overestimate in some implementations. For full details of the workspace required by this routine please refer to the Users' Note for your implementation.

On exit: the real part of $WORK(1)$ contains the minimum workspace required for the current value of N with this implementation.

5: $IFAIL$ – INTEGER *Input/Output*

On entry: $IFAIL$ must be set to 0, -1 or 1 . If you are unfamiliar with this parameter you should refer to Section 3.3 in the Essential Introduction for details.

On exit: $IFAIL = 0$ unless the routine detects an error (see Section 6).

For environments where it might be inappropriate to halt program execution when an error is detected, the value -1 or 1 is recommended. If the output of error messages is undesirable, then the value 1 is recommended. Otherwise, if you are not familiar with this parameter, the recommended value is 0 . **When the value -1 or 1 is used it is essential to test the value of $IFAIL$ on exit.**

6 Error Indicators and Warnings

If on entry $IFAIL = 0$ or -1 , explanatory error messages are output on the current error message unit (as defined by X04AAF).

Errors or warnings detected by the routine:

$IFAIL = 1$

On entry, $N < 1$.

$IFAIL = 2$

On entry, $DIRECT \neq 'F'$ or $'B'$.

$IFAIL = 3$

On entry, N has more than 30 prime factors.

$IFAIL = 4$

An unexpected error has occurred in an internal call. Check all subroutine calls and array dimensions. Seek expert help.

7 Accuracy

Some indication of accuracy can be obtained by performing a subsequent inverse transform and comparing the results with the original sequence (in exact arithmetic they would be identical).

8 Further Comments

The time taken is approximately proportional to $n \times \log n$, but also depends on the factorization of n . C06PCF is faster if the only prime factors of n are 2, 3 or 5; and fastest of all if n is a power of 2.

9 Example

This example reads in a sequence of complex data values and prints their discrete Fourier transform (as computed by C06PCF with DIRECT = 'F'). It then performs an inverse transform using C06PCF with DIRECT = 'B', and prints the sequence so obtained alongside the original data values.

9.1 Program Text

```
*      C06PCF Example Program Text
*      Mark 19 Release. NAG Copyright 1999.
*      .. Parameters ..
      INTEGER          NIN, NOUT
      PARAMETER        (NIN=5,NOUT=6)
      INTEGER          NMAX
      PARAMETER        (NMAX=20)
*      .. Local Scalars ..
      INTEGER          IFAIL, J, N
*      .. Local Arrays ..
      COMPLEX *16      WORK(2*NMAX+15), X(0:NMAX-1), XX(0:NMAX-1)
*      .. External Subroutines ..
      EXTERNAL         C06PCF
*      .. Intrinsic Functions ..
      INTRINSIC        AIMAG, DBLE
*      .. Executable Statements ..
      WRITE (NOUT,*) 'C06PCF Example Program Results'
*      Skip heading in data file
      READ (NIN,*)
20  CONTINUE
      READ (NIN,*,END=100) N
      IF (N.GT.1 .AND. N.LE.NMAX) THEN
        DO 40 J = 0, N - 1
          READ (NIN,*) X(J)
          XX(J) = X(J)
40    CONTINUE
      IFAIL = 1

*      CALL C06PCF('F',X,N,WORK,IFAIL)

*      IF (IFAIL.EQ.0) THEN
        WRITE (NOUT,*)
        WRITE (NOUT,*) 'Components of discrete Fourier transform'
        WRITE (NOUT,*)
        WRITE (NOUT,*) '          Real          Imag'
        WRITE (NOUT,*)
        DO 60 J = 0, N - 1
          WRITE (NOUT,99999) J, DBLE(X(J)), AIMAG(X(J))
60    CONTINUE
*      CALL C06PCF('B',X,N,WORK,IFAIL)

*      WRITE (NOUT,*)
      WRITE (NOUT,*)
+      'Original sequence as restored by inverse transform'
      WRITE (NOUT,*)
      WRITE (NOUT,*)
+      '          Original          Restored'
+      '          Real          Imag          Real          Imag'
      WRITE (NOUT,*)
      DO 80 J = 0, N - 1
        WRITE (NOUT,99999) J, XX(J), X(J)
80    CONTINUE
      GO TO 20
```

```

      ELSE
        WRITE (NOUT,*)
        WRITE (NOUT,99998) ' ** C06PCF returned with IFAIL = ',
+       IFAIL
      END IF
    ELSE
      WRITE (NOUT,*) 'Invalid value of N'
    END IF
  100 CONTINUE
*
99999 FORMAT (1X,I5,2(:5X,'(',F8.5,',',F8.5,')'))
99998 FORMAT (1X,A,I5)
      END

```

9.2 Program Data

C06PCF Example Program Data

```

7
(0.34907, -0.37168)
(0.54890, -0.35669)
(0.74776, -0.31175)
(0.94459, -0.23702)
(1.13850, -0.13274)
(1.32850,  0.00074)
(1.51370,  0.16298)

```

9.3 Program Results

C06PCF Example Program Results

Components of discrete Fourier transform

	Real	Imag
0	(2.48361,-0.47100)	
1	(-0.55180, 0.49684)	
2	(-0.36711, 0.09756)	
3	(-0.28767,-0.05865)	
4	(-0.22506,-0.17477)	
5	(-0.14825,-0.30840)	
6	(0.01983,-0.56496)	

Original sequence as restored by inverse transform

	Original		Restored	
	Real	Imag	Real	Imag
0	(0.34907,-0.37168)		(0.34907,-0.37168)	
1	(0.54890,-0.35669)		(0.54890,-0.35669)	
2	(0.74776,-0.31175)		(0.74776,-0.31175)	
3	(0.94459,-0.23702)		(0.94459,-0.23702)	
4	(1.13850,-0.13274)		(1.13850,-0.13274)	
5	(1.32850, 0.00074)		(1.32850, 0.00074)	
6	(1.51370, 0.16298)		(1.51370, 0.16298)	
