

NAG Library Routine Document

F07VSF (ZTBTRS)

Note: before using this routine, please read the Users' Note for your implementation to check the interpretation of ***bold italicised*** terms and other implementation-dependent details.

1 Purpose

F07VSF (ZTBTRS) solves a complex triangular band system of linear equations with multiple right-hand sides, $AX = B$, $A^T X = B$ or $A^H X = B$.

2 Specification

```
SUBROUTINE F07VSF(UPLO, TRANS, DIAG, N, KD, NRHS, AB, LDAB, B, LDB,
1                      INFO)
INTEGER                N, KD, NRHS, LDAB, LDB, INFO
complex*16           AB(LDAB,*), B(LDB,*)
CHARACTER*1            UPLO, TRANS, DIAG
```

The routine may be called by its LAPACK name ***ztbtrs***.

3 Description

F07VSF (ZTBTRS) solves a complex triangular band system of linear equations $AX = B$, $A^T X = B$ or $A^H X = B$.

4 References

Golub G H and Van Loan C F (1996) *Matrix Computations* (3rd Edition) Johns Hopkins University Press, Baltimore

Higham N J (1989) The accuracy of solutions to triangular systems *SIAM J. Numer. Anal.* **26** 1252–1265

5 Parameters

- 1: UPLO – CHARACTER*1 *Input*
On entry: indicates whether A is upper or lower triangular.
UPLO = 'U'
 A is upper triangular.
UPLO = 'L'
 A is lower triangular.
Constraint: UPLO = 'U' or 'L'.
- 2: TRANS – CHARACTER*1 *Input*
On entry: indicates the form of the equations
TRANS = 'N'
The equations are of the form $AX = B$.
TRANS = 'T'
The equations are of the form $A^T X = B$.

TRANS = 'C'

The equations are of the form $A^H X = B$.

Constraint: TRANS = 'N', 'T' or 'C'.

3: DIAG – CHARACTER*1

Input

On entry: indicates whether A is a nonunit or unit triangular matrix.

DIAG = 'N'

A is a nonunit triangular matrix.

DIAG = 'U'

A is a unit triangular matrix; the diagonal elements are not referenced and are assumed to be 1.

Constraint: DIAG = 'N' or 'U'.

4: N – INTEGER

Input

On entry: n , the order of the matrix A .

Constraint: $N \geq 0$.

5: KD – INTEGER

Input

On entry: k_d , the number of superdiagonals of the matrix A if UPLO = 'U', or the number of subdiagonals if UPLO = 'L'.

Constraint: $KD \geq 0$.

6: NRHS – INTEGER

Input

On entry: r , the number of right-hand sides.

Constraint: NRHS ≥ 0 .

7: AB(LDAB,*) – **complex*16** array

Input

Note: the second dimension of the array AB must be at least $\max(1, N)$.

On entry: the n by n triangular band matrix A .

The matrix is stored in rows 1 to $k_d + 1$, more precisely,

if UPLO = 'U', the elements of the upper triangle of A within the band must be stored with element A_{ij} in $AB(k_d + 1 + i - j, j)$ for $\max(1, j - k_d) \leq i \leq j$;

if UPLO = 'L', the elements of the lower triangle of A within the band must be stored with element A_{ij} in $AB(1 + i - j, j)$ for $j \leq i \leq \min(n, j + k_d)$.

If DIAG = 'U', the diagonal elements of A are assumed to be 1, and are not referenced.

8: LDAB – INTEGER

Input

On entry: the first dimension of the array AB as declared in the (sub)program from which F07VSF (ZTBTRS) is called.

Constraint: LDAB $\geq KD + 1$.

9: B(LDB,*) – **complex*16** array

Input/Output

Note: the second dimension of the array B must be at least $\max(1, NRHS)$.

On entry: the n by r right-hand side matrix B .

On exit: the n by r solution matrix X .

- 10: LDB – INTEGER *Input*
On entry: the first dimension of the array B as declared in the (sub)program from which F07VSF (ZTBTRS) is called.
Constraint: $LDB \geq \max(1, N)$.
- 11: INFO – INTEGER *Output*
On exit: INFO = 0 unless the routine detects an error (see Section 6).

6 Error Indicators and Warnings

Errors or warnings detected by the routine:

INFO < 0

If $\text{INFO} = -i$, the i th parameter had an illegal value. An explanatory message is output, and execution of the program is terminated.

INFO > 0

If $\text{INFO} = i$, $a(i, i)$ is exactly zero; A is singular and the solution has not been computed.

7 Accuracy

The solutions of triangular systems of equations are usually computed to high accuracy. See Higham (1989).

For each right-hand side vector b , the computed solution x is the exact solution of a perturbed system of equations $(A + E)x = b$, where

$$|E| \leq c(k)\epsilon|A|,$$

$c(k)$ is a modest linear function of k , and ϵ is the *machine precision*.

If $\hat{x}$ is the true solution, then the computed solution x satisfies a forward error bound of the form

$$\frac{\|x - \hat{x}\|_\infty}{\|x\|_\infty} \leq c(k) \text{cond}(A, x)\epsilon, \quad \text{provided} \quad c(k) \text{cond}(A, x)\epsilon < 1,$$

where $\text{cond}(A, x) = \|A^{-1}\|_\infty \|A\|_\infty \|x\|_\infty / \|x\|_\infty$.

Note that $\text{cond}(A, x) \leq \text{cond}(A) = \|A^{-1}\|_\infty \|A\|_\infty \leq \kappa_\infty(A)$; $\text{cond}(A, x)$ can be much smaller than $\text{cond}(A)$ and it is also possible for $\text{cond}(A^H)$, which is the same as $\text{cond}(A^T)$, to be much larger (or smaller) than $\text{cond}(A)$.

Forward and backward error bounds can be computed by calling F07VVF (ZTBRFS), and an estimate for $\kappa_\infty(A)$ can be obtained by calling F07VUF (ZTBCON) with NORM = 'I'.

8 Further Comments

The total number of real floating-point operations is approximately $8nkr$ if $k \ll n$.

The real analogue of this routine is F07VEF (DTBTRS).

9 Example

This example solves the system of equations $AX = B$, where

$$A = \begin{pmatrix} -1.94 + 4.43i & 0.00 + 0.00i & 0.00 + 0.00i & 0.00 + 0.00i \\ -3.39 + 3.44i & 4.12 - 4.27i & 0.00 + 0.00i & 0.00 + 0.00i \\ 1.62 + 3.68i & -1.84 + 5.53i & 0.43 - 2.66i & 0.00 + 0.00i \\ 0.00 + 0.00i & -2.77 - 1.93i & 1.74 - 0.04i & 0.44 + 0.10i \end{pmatrix}$$

and

$$B = \begin{pmatrix} -8.86 - 3.88i & -24.09 - 5.27i \\ -15.57 - 23.41i & -57.97 + 8.14i \\ -7.63 + 22.78i & 19.09 - 29.51i \\ -14.74 - 2.40i & 19.17 + 21.33i \end{pmatrix}.$$

Here A is treated as a lower triangular band matrix with two subdiagonals.

9.1 Program Text

```

*      F07VSF Example Program Text
*      Mark 15 Release. NAG Copyright 1991.
*      .. Parameters ..
      INTEGER          NIN, NOUT
      PARAMETER        (NIN=5,NOUT=6)
      INTEGER          NMAX, KDMAX, LDAB, NRHMAX, LDB
      PARAMETER        (NMAX=8,KDMAX=NMAX,LDAB=KDMAX+1,NRHMAX=NMAX,
+                      LDB=NMAX)
      CHARACTER        TRANS, DIAG
      PARAMETER        (TRANS='N',DIAG='N')
*      .. Local Scalars ..
      INTEGER          I, IFAIL, INFO, J, KD, N, NRHS
      CHARACTER        UPLO
*      .. Local Arrays ..
      COMPLEX *16      AB(LDAB,NMAX), B(LDB,NRHMAX)
      CHARACTER        CLABS(1), RLABS(1)
*      .. External Subroutines ..
      EXTERNAL         X04DBF, ZTBTRS
*      .. Intrinsic Functions ..
      INTRINSIC        MAX, MIN
*      .. Executable Statements ..
      WRITE (NOUT,*) 'F07VSF Example Program Results'
*      Skip heading in data file
      READ (NIN,*)
      READ (NIN,*) N, KD, NRHS
      IF (N.LE.NMAX .AND. KD.LE.KDMAX .AND. NRHS.LE.NRHMAX) THEN
*
*      Read A and B from data file
*
      READ (NIN,*) UPLO
      IF (UPLO.EQ.'U') THEN
        DO 20 I = 1, N
          READ (NIN,*) (AB(KD+1+I-J,J),J=I,MIN(N,I+KD))
20      CONTINUE
      ELSE IF (UPLO.EQ.'L') THEN
        DO 40 I = 1, N
          READ (NIN,*) (AB(1+I-J,J),J=MAX(1,I-KD),I)
40      CONTINUE
      END IF
      READ (NIN,*) ((B(I,J),J=1,NRHS),I=1,N)
*
*      Compute solution
*
      CALL ZTBTRS(UPLO,TRANS,DIAG,N,KD,NRHS,AB,LDAB,B,LDB,INFO)
*
*      Print solution
*
      WRITE (NOUT,*)
      IF (INFO.EQ.0) THEN
        IFAIL = 0
        CALL X04DBF('General',' ',N,NRHS,B,LDB,'Bracketed','F7.4',
+                  'Solution(s)','Integer',RLABS,'Integer',CLABS,
+                  80,0,IFAIL)
      ELSE

```

```

        WRITE (NOUT,*) 'A is singular'
      END IF
    END IF
  *
  END

```

9.2 Program Data

F07VSF Example Program Data

```

  4  2  2                                     :Values of N, KD and NRHS
  'L'                                         :Value of UPLO
(-1.94, 4.43)
(-3.39, 3.44) ( 4.12,-4.27)
( 1.62, 3.68) (-1.84, 5.53) ( 0.43,-2.66)
              (-2.77,-1.93) ( 1.74,-0.04) ( 0.44, 0.10) :End of matrix A
( -8.86, -3.88) (-24.09, -5.27)
(-15.57,-23.41) (-57.97,  8.14)
( -7.63, 22.78) ( 19.09,-29.51)
(-14.74, -2.40) ( 19.17, 21.33)                :End of matrix B

```

9.3 Program Results

F07VSF Example Program Results

```

Solution(s)
              1              2
1  ( 0.0000, 2.0000) ( 1.0000, 5.0000)
2  ( 1.0000,-3.0000) (-7.0000,-2.0000)
3  (-4.0000,-5.0000) ( 3.0000, 4.0000)
4  ( 2.0000,-1.0000) (-6.0000,-9.0000)

```
